

PART NUMBER	RATED VOLTS	KVAR	HORSE POWER	AMPS	HEIGHT	WIDTH	DEPTH	ENCL TYPE	WATTS LOSS	WEIGHT	WEIGHT with Fuse Monitor
HGP0005AW3C0000	480	1.2	5	7.6	33.24	33	13.73	3R	150	101	103
HGP0008AW3C0000	480	3	7.5	11	33.24	33	13.73	3R	150	106	108
HGP0010AW3C0000	480	3	10	14	33.24	33	13.73	3R	175	113	115
HGP0015AW3C0000	480	5	15	21	33.24	33	13.73	3R	250	126	128
HGP0020AW3C0000	480	6	20	27	33.24	33	13.73	3R	275	126	128
HGP0025AW3C0000	480	8	25	34	33.24	33	13.73	3R	250	131	133
HGP0030AW3C0000	480	10	30	40	33.24	33	13.73	3R	300	145	147
HGP0040AW3C0000	480	15	40	52	37.58	39.15	13.73	3R	500	221	223
HGP0050AW3C0000	480	15	50	65	37.58	39.15	13.73	3R	550	231	233
HGP0060AW3C0000	480	20	60	77	37.58	39.15	13.73	3R	675	241	243
HGP0075AW3C0000	480	25	75	96	37.58	39.15	13.73	3R	650	248	250
HGP0100AW3C0000	480	30	100	124	37.58	39.15	13.73	3R	750	271	273
HGP0125AW3C0000	480	40	125	156	37.58	39.15	13.73	3R	1000	291	293
HGP0150AW3C0000	480	45	150	180	52.58	39.07	17.73	3R	1200	405	407
HGP0200AW3C0000	480	60	200	240	52.58	39.07	17.73	3R	1600	475	477
HGP0250AW3C0000	480	75	250	302	53.86	45.14	21.73	3R	1800	555	557
HGP0300AW3C0000	480	90	300	361	53.86	45.14	21.73	3R	2100	620	622
HGP0350AW3C0000	480	105	350	414	53.86	45.14	21.73	3R	2200	670	672
HGP0400AW3C0000	480	120	400	477	65.77	57.13	26.32	3R	2600	995	1005
HGP0450AW3C0000	480	135	450	515	65.77	57.13	26.32	3R	2800	1004	1006
HGP0500AW3C0000	480	150	500	590	65.77	57.13	26.32	3R	3100	1019	1021
HGP0600AW3C0000	480	180	600	720	65.77	57.13	26.32	3R	2700	1244	1255
HGP0700AW3C0000	480	210	700	840	65.77	57.42	26.32	3R	2900	1400	1402
HGP0800AW3C0000	480	240	800	960	65.77	57.42	26.32	3R	3000	1600	1602
HGP0900AW3C0000	480	270	900	1080	80.22	72.06	30	3R	3300	3048	3050

*Note- Products with fuse monitor will have "F" replace "C" in part number