

PART NUMBER	RATED VOLTS	KVAR	HORSE POWER	AMPS	HEIGHT	WIDTH	DEPTH	ENCL TYPE	WATTS LOSS	WEIGHT	WEIGHT with Fuse Monitor
HGP0015CW3S0000	600	5	15	17	32.24	33	13.73	3R	300	135	137
HGP0030CW3S0000	600	10	30	32	32.24	33	13.73	3R	425	154	156
HGP0040CW3S0000	600	15	40	41	36	39.15	13.73	3R	675	239	241
HGP0050CW3S0000	600	15	50	52	36	39.15	13.73	3R	700	249	251
HGP0060CW3S0000	600	20	60	62	36	39.15	13.73	3R	900	259	261
HGP0075CW3S0000	600	25	75	77	36	39.15	13.73	3R	1000	269	271
HGP0100CW3S0000	600	30	100	99	36	39.15	13.73	3R	1050	269	271
HGP0125CW3S0000	600	40	125	125	36	39.15	13.73	3R	1200	289	291
HGP0150CW3S0000	600	45	150	144	51	39.07	17.73	3R	1500	432	434
HGP0200CW3S0000	600	60	200	192	51	39.07	17.73	3R	1850	480	482
HGP0250CW3S0000	600	75	250	242	51	45.14	21.73	3R	2000	580	582
HGP0300CW3S0000	600	90	300	289	51	45.14	21.73	3R	2500	736	738
HGP0350CW3S0000	600	105	350	336	64	57.13	25.96	3R	2800	956	968
HGP0400CW3S0000	600	120	400	382	64	57.13	25.96	3R	2700	966	968
HGP0450CW3S0000	600	135	450	412	64	57.13	25.96	3R	3050	976	978
HGP0500CW3S0000	600	150	500	472	64	57.13	25.96	3R	3000	1161	1173
HGP0600CW3S0000	600	180	600	576	64	57.13	25.96	3R	3200	1176	1189

*Note- Products with fuse monitor will have "G" replace "S" in part number