

PART NUMBER	RATED VOLTS	KVAR	HORSE POWER	AMPS	HEIGHT	WIDTH	DEPTH	ENCL TYPE	WATTS LOSS	WEIGHT	WEIGHT with Fuse Monitor
HGP0005AWOC0000	480	1.2	5	7.6	19.75	17	9.79	N/A	150	40	42
HGP0008AWOC0000	480	3	7.5	11	19.75	17	9.79	N/A	150	45	47
HGP0010AWOC0000	480	3	10	14	19.75	17	9.79	N/A	175	45	47
HGP0015AWOC0000	480	5	15	21	19.75	17	10.14	N/A	250	55	57
HGP0020AWOC0000	480	6	20	27	19.75	17	10.14	N/A	275	60	62
HGP0025AWOC0000	480	8	25	34	19.75	17	10.65	N/A	250	67	69
HGP0030AWOC0000	480	10	30	40	30.75	17	11.38	N/A	300	85	87
HGP0040AWOC0000	480	15	40	52	30.75	17	11.5	N/A	500	125	127
HGP0050AWOC0000	480	15	50	65	30.75	17	11.5	N/A	550	135	137
HGP0060AWOC0000	480	20	60	77	30.75	17	11.5	N/A	675	140	142
HGP0075AWOC0000	480	25	75	96	30.75	17	11.5	N/A	650	145	147
HGP0100AWOC0000	480	30	100	124	56	17	11.5	N/A	750	205	207
HGP0125AWOC0000	480	40	125	156	56	17	13.13	N/A	1000	225	227
HGP0150AWOC0000	480	45	150	180	56	17	13.13	N/A	1200	265	267
HGP0200AWOC0000	480	60	200	240	67	17	13.5	N/A	1600	350	352
HGP0250AWOC0000	480	75	250	302	67	17	13.5	N/A	1800	360	362
HGP0300AWOC0000	480	90	300	361	67	17.31	14.5	N/A	2100	490	492
HGP0350AWOC0000	480	105	350	414	40	41.21	20.53	N/A	2200	640	642
HGP0400AWOC0000	480	120	400	477	40	41.21	20.53	N/A	2600	690	700

\*Note- Products with fuse monitor will have "F" replace "C" in part number